

CISCO/Linksys 112 SPA

Aby skonfigurować bramkę należy:

1. z klawiatury telefonu podłączonego do bramki wybrać ***** oraz 110# i odsłuchać adres IP,
2. zalogować się do konfiguratora bramki wpisując w przeglądarce jej adres IP,
3. Wpisać w user:admin i hasło: admin
4. Na pierwszym ekranie wpisać następujące parametry w Line1

Proxy: sip.easycall.pl

Display Name/Name: [6-cio cyfrowy identyfikator użytkownika]

User ID: [6-cio cyfrowy identyfikator użytkownika]

Password: [hasło użytkownika]

Register Expires: 180 sekund lub 3 minuty

5. Po wpisaniu tych parametrów klikamy na dole przycisk SUBMIT.

6. Następnie klikamy na zakładkę Voice potem Line1 i ustawiamy:

Line enable: Yes

NAT Mapping Enable: Yes

NAT Keep Alive Enable: Yes

Kolejny raz klikamy SUBMIT.

The screenshot displays the Cisco Phone Adapter Configuration Utility web interface. The top navigation bar includes 'Quick Setup', 'Network Setup', 'Voice' (highlighted), 'Administration', and 'Status'. The left sidebar shows a tree view with 'Line 1' selected. The main content area is titled 'Line 1' and contains several configuration sections:

- Auth INVITE:** no
- Use Anonymous With RPID:** yes
- Reply 182 On Call Waiting:** no
- Use Local Addr In FROM:** no
- Call Feature Settings:**
 - Blind Attn-Xfer Enable:** no
 - Xfer When Hangup Conf:** yes
 - Conference Bridge Ports:** 3
 - Emergency Number:** [text input]
 - MOH Server:** [text input]
 - Conference Bridge URL:** [text input]
 - Enable IP Dialing:** no
 - Mailbox ID:** [text input]
- Proxy and Registration:**
 - Proxy:** [text input]
 - Outbound Proxy:** [text input]
 - Use Outbound Proxy:** yes
 - Register:** yes
 - Register Expires:** [text input]
 - Use DNS SRV:** no
 - Proxy Fallback Intvl:** [text input]
 - Mailbox Subscribe URL:** [text input]
 - Use OB Proxy In Dialog:** yes
 - Make Call Without Reg:** no
 - Ans Call Without Reg:** no
 - DNS SRV Auto Prefix:** no
 - Proxy Redundancy Method:** Normal
 - Mailbox Subscribe Expires:** [text input]
- Subscriber Information:**
 - Display Name:** [text input]
 - Password:** [text input]
 - User ID:** [text input]
 - Use Auth ID:** no

At the bottom of the configuration area are buttons for 'Submit', 'Cancel', and 'Refresh'. The footer contains the copyright notice '© 2012 Cisco Systems, Inc. All Rights Reserved.' and the identifier 'SPA122'.